



Evolution Wireless Digital EW-D SKM-S | Handheld Transmitter



Rugged and versatile handheld transmitter for use with Evolution Wireless Digital receivers, compatible with a wide range of Sennheiser and Neumann microphone capsules.

Versatile and feature-rich digital wireless system for those who sing, speak or play instruments that allows for seamless product pairing and management via the EW-D Smart Assist App.

FEATURES

- Digital wireless eliminates noise, interference and static bursts
- UHF transmission greatly enhances range, reliability and scalability
- Mobile App streamlines setup and operation and eliminates complicated menus
- Automated setup creates reliable connections with minimal time and effort
- Up to 2,240 selectable frequencies
- 56 MHz Bandwidth will allow for up to 90 channels
- Preserves every detail of even the most dynamic performances with 134 dB transmitter dynamic range
- Compatible with a wide range of Sennheiser and Neumann microphone capsules
- Lithium Ion battery pack delivers up to 12 hours of operation (up to 8 hours of operation with AA batteries)
- All metal housing

DELIVERY INCLUDES

- EW-D SKM-S handheld transmitter
- MMD 835 microphone module
- MZQ 1 microphone clamp
- pouch
- quick guide
- safety guide
- manufacturer declaration sheet

PRODUCT VARIANTS

EW-D SKM-S (Q1-6)	470.2 - 526 MHz	Art. no. 508790
EW-D SKM-S (R1-6)	520 - 576 MHz	Art. no. 508791
EW-D SKM-S (R4-9)	552 - 607.8 MHz	Art. no. 508792
EW-D SKM-S (S1-7)	606.2 - 662 MHz	Art. no. 508793
EW-D SKM-S (S4-7)	630 - 662 MHz	Art. no. 508794
EW-D SKM-S (S7-10)	662 - 693.8 MHz	Art. no. 508795
EW-D SKM-S (U1/5)	823.2 - 831.8 MHz & 863.2 - 864.8 MHz	Art. no. 508796
EW-D SKM-S (V3-4)	925.2 - 937.3 MHz	Art. no. 508798
EW-D SKM-S (Y1-3)	1785.2 - 1799.8 MHz	Art. no. 508799



Evolution Wireless Digital

EW-D SKM-S | Handheld Transmitter

ACCESSORIES

EW-D ASA (Q-R-S)	Active Antenna Splitter	470 - 694 MHz	Art. no. 508879
EW-D ASA (T-U-V-W)	Active Antenna Splitter	694 - 1075 MHz	Art. no. 508880
EW-D ASA (X-Y)	Active Antenna Splitter	1350 - 1805 MHz	Art. no. 508881
EW-D ASA CN/ANZ (Q-R-S)	Active Antenna Splitter	470 - 694 MHz	Art. no. 508998
EW-D AB (Q)	Antenna Booster	470 - 550 MHz	Art. no. 508873
EW-D AB (R)	Antenna Booster	520 - 608 MHz	Art. no. 508874
EW-D AB (S)	Antenna Booster	606 - 694 MHz	Art. no. 508875
EW-D AB (U)	Antenna Booster	823 - 865 MHz	Art. no. 508876
EW-D AB (V)	Antenna Booster	902 - 960 MHz	Art. no. 508877
EW-D AB (Y)	Antenna Booster	1785 - 1805 MHz	Art. no. 508878
ADP UHF (470 - 1075 MHz)	Passive directional antenna	470 - 1075 MHz	Art. no. 508863
BA 70	Rechargeable battery pack for SK and SKM		Art. no. 508860
L 70 USB	Charger for BA 70 rechargeable battery pack		Art. no. 508861
EW-D CHARGING SET	Set of L 70 USB charger and 2 BA 70 rechargeable battery packs		Art. no. 508862
EW-D COLOR CODING SET	Colored labels for wireless link identification for EM, SKM-S, SK		Art. no. 508989
EW-D SK COLOR CODING	Colored labels for wireless link identification for SK		Art. no. 508990
EW-D SKM COLOR CODING	Colored labels for wireless link identification for SKM-S		Art. no. 508991
EW-D EM COLOR CODING	Colored labels for wireless link identification for EM		Art. no. 508992



Evolution Wireless Digital EW-D SKM-S | Handheld Transmitter

DIMENSIONS

